

Next PG2/ Next-K9 PG2

Two-way
Wireless PIR/
Pet-immune
Motion
Detectors



- PowerG® two-way Frequency Hopping Spread Spectrum FHSS-TDMA technology provides robustness and reliability closer than ever to wired
- 15m (50ft) 90° multiple-curtain coverage with "wall" creep zone
- Pet tolerant model (Next-K9 PG2) ignores pets weighing up to 38kg (85lb)
- Large transmission range enabling repeater-free installations
- Longer battery life (up to 6 years with typical use)
- Visible signal quality indication shown on the device
- Enhanced false alarm immunity by combined Fresnel and cylindrical optics
- Visible and transmitted low battery indication
- Compatible with PowerMaster systems and PowerG receivers

Next® PG2 and Next-K9 PG2 are two-way wireless digital PIR detectors which are compatible with PowerMaster® alarm systems. Based on Visonic's ground-breaking PowerG technology, these detectors combine several field-proven advanced technologies which deliver longer transmission range and battery life, as well as unmatched advan-tages for professional installers, central monitoring stations and end-users alike.

Specifications:

Battery type: 3V, CR-123A

Lithium battery

Weight 70g (2.5oz)

(including battery):

Operating -10°C to 50°C temperature: (14°F to 122°F)

Operating Indoor

environment:

Dimensions: 94.5 x 63.5 x 53mm

(3.7 x 2.5 x 2.06in)